

WEB: www.aawcs.co.uk EMAIL: aaw@aawcs.co.uk TEL: 01635 248589

Unit 10 Langley Business Court, Beedon, Newbury, Berkshire, RG20 8RY

Customer Help Sheet:

Re-starting the unit

Introduction

From time to time it may be necessary to re-start a RIOT-S – for example if it has lost connection with the network.

Instructions

1. Press the time in the top right corner of the screen.

Inputs	Home Ba	ck 1212
Name	Reading	Status
Fridge 1 Core	4.2	ок
Fridge 1 Air	5.3	ок
Fridge 2 Core	3.7	ок
Fridge 2 Air	3.2	ок
Freezer 1	-21.5	ок
Freezer 2	-37.4	ок
HACCP	26.2	ок

The 'Setup' menu will be displayed.

NOTE: If you are not already logged on as a user then you will be prompted to do so. To re-start the RIOT-S you will need to log on as a user with a "service" access level.

Press the 'Service Menu' button.

Setup	Home Back 12:23	
Alm Templates	Logoff now	
Actions	Contacts / Users	
Schedules	Set Time	
Input List	Service Menu	
System Config	Sounds Menu	
Print Log	Touch Calibrate	

The 'Service' menu will be displayed.

3. Press the 'Battery' button.

Service	Home Back 12:23	
IT Settings	USB Backup	
TCPIP Status		
	PSTN Modem	
	System Alarm	
Battquy	Raw Inputs	
S/W Version	AAW Config	

The 'Battery' parameters will be displayed.

WEB: www.aawcs.co.uk EMAIL: aaw@aawcs.co.uk TEL: 01635 248589

Customer Help Sheet: Re-starting the unit

4. Press the setting for the 'Kill Power' parameter.




An 'Edit' screen will be displayed showing the current setting for the selected parameter.

5. Press the 'Shutdown' option, then press 'Ent'.



The RIOT-S will be turned off.

6. Wait for the RIOT-S to turn itself back on.



Inputs	Home Ba	ck 12:23
Name	Reading	Status
Fridge 1 Core	4.2	ок
Fridge 1 Air	5.3	ок
Fridge 2 Core	3.7	ок
Fridge 2 Air	3.2	ок
Freezer 1	-21.5	ок
Freezer 2	-37.4	ок
HACCP	26.2	ок

Provided that the RIOT-S has mains power, it will turn itself back on after 5 – 10 seconds and display the 'Home' screen.

If the RIOT-S does not have mains power, then it will turn itself back on when it is next connected to mains power.

NOTE: After the RIOT-S has turned itself back on it may take several minutes for all the readings and statuses to be updated/shown.